



ENGINEERING & MANAGEMENT EXAMINATIONS, JUNE - 2007
ELECTROMAGNETIC WAVES & RADIATING SYSTEMS
SEMESTER - 4

Time : 3 Hours]

[Full Marks : 70

Group - A

(Multiple Choice Type Questions)

1. Choose the correct alternatives for any ten of the following : 10 × 1 = 10

i) The magnetic flux density \vec{B} and vector potential \vec{A} are related as

a) $\vec{B} = \nabla \times \vec{A}$

b) $\vec{A} = \nabla \times \vec{B}$

c) $\vec{B} = \nabla \cdot \vec{A}$

d) $\vec{A} = \nabla \cdot \vec{B}$

ii) A potential field is given by $V = 3x^2y - yz$. The electric field at $P(2, -1, 4)$ is

a) $12\vec{i} - 8\vec{j}$ V/m

b) $12\vec{i} - \vec{j}$ V/m

c) $12\vec{i} + 8\vec{j} + \vec{k}$ V/m

d) $-12\vec{i} - 8\vec{j} - \vec{k}$ V/m.

iii) The electric field lines & equipotential lines

a) are parallel to each other

b) are one and the same

c) cut each other orthogonally

d) can be inclined to each other at any angle.

iv) A transmission line of length $\frac{\lambda}{4}$ shorted at far end behaves like

a) series resonant circuit

b) parallel resonant circuit

c) pure inductor

d) pure capacitor.

v) Maxwell's equation $\nabla \times \vec{H} = \vec{J} + \dot{\vec{D}}$ represents

a) Gauss's law in magnetism

b) Kirchhoff's current law for direct current

c) Biot-Savart law

d) Generalized Ampere's circuital law.



- vi) In a two region system, a plane wave is arriving at a normal incidence in air with amplitude $E_1 = 100 \text{ V/m}$ and frequency 100 MHz . The slab is Teflon ($\epsilon_r = 2.1$, $\epsilon''/\epsilon' = 0$). The amplitude of the reflected wave is
- a) 18.34 V/m b) 36.68 V/m
 c) -18.34 V/m d) -36.68 V/m .
- vii) If the frequency of the incident wave increases by a factor of 4, the depth to which a wave penetrates a conducting material
- a) increases by a factor of 2 b) increases by a factor of 4
 c) decreases by a factor of 2 d) decreases by a factor of 4.
- viii) The MUF of transmission between two stations 500 km apart at $f_{crit} = 9 \text{ MHz}$ and minimum value of incident angle $i = 45^\circ$ is
- a) 0.7 MHz b) 25.4 MHz
 c) 12.7 MHz d) 18 MHz .
- ix) A quarter-wave monopole antenna operating in air at a frequency of 1 MHz must have an overall length (l) of
- a) $l \gg \lambda$ b) 150 m
 c) 75 m d) $l \ll \lambda$.
- x) The radiation resistance of a dipole, having a length of 4 cm , radiating 50 W of power at a frequency of 500 MHz is
- a) 3.5Ω b) 0.82Ω
 c) 1.75Ω d) 7.0Ω .
- xi) Ohm's law is obeyed by
- a) conduction current b) convection current
 c) conduction & convection current d) none of these.
- xii) The direction of propagation of EM wave is obtained from
- a) $E \times H$ b) $E \cdot H$
 c) E d) H .

**Group - B****(Short Answer Type Questions)**

Answer any three questions.

3 × 5 = 15

2. Define the term i) VSWR and ii) 'Reflection co-efficient' for transmission line.

Explain the relationship between them.

3. Prove that $\nabla \times \vec{H} = \vec{J} + \frac{\partial \vec{D}}{\partial t}$. The symbols have usual meaning.

4. A 2m long lossless transmission line has an impedance of 300Ω . The velocity of propagation is 2.5×10^8 m/s. The load has an impedance of 300Ω with sending end voltage being 60V at 100 MHz. Find :

- a) The phase constant
- b) The load voltage
- c) The load current
- d) The load reflection coefficient &
- e) Standing wave ratio.

5. Why is ionosphere important for radiowave propagation? Describe the different layers of ionosphere.

6. What do you mean by magnetic vector potential? Write down the Maxwell's equations for time varying electromagnetic fields, when the medium is lossless, linear, isotropic, homogeneous and source free.

3 + 2



Group - C

(Long Answer Type Questions)

Answer any three questions.

3 × 15 = 45

7. a) Find the expression of Radiation resistance of a short electric dipole with uniform current distribution. 7
- b) Define complex Poynting vector. 3
- c) Explain the concept of skin depth & find out an expression for that. 5
8. a) Derive an expression for the input impedance Z_{in} of a lossless transmission line, in terms of relevant parameters, when the line is terminated in load impedance Z_L . 6
- b) Show that for a lossless transmission line the impedance of a line repeats over every $\frac{\lambda}{2}$ distance. 5
- c) A transmission line with air as dielectric has $Z_0 = 50\Omega$ and a phase constant of 3 rad/m at 10 MHz. Find the inductance & capacitance of the line. 4
9. a) What is electromagnetic interference ? 2
- b) Why does the short wave radio signal propagate with very low attenuation at night ? Describe the sky-wave propagation of EM waves. 3 + 6
- c) What is fading ? Briefly describe the diversity techniques to reduce the effect of fading. 1 + 3
10. a) Obtain the Poynting theorem for the conservation of energy in an electromagnetic field and discuss the physical significance of each term in resulting equation. 6
- b) In free space $E(z, t) = 50 \cos(\omega t - \beta z)$ V/m. Find the average power crossing a circular area of radius 5m in the plane $x = \text{constant}$. 5
- c) Derive the equation of continuity for time varying fields. 4
11. a) State & explain Faraday's law. 4
- b) Derive the induced *emf* when a stationary loop is in the time varying *B* fields. 4
- c) Determine the magnetic field intensity at a point *P* due to a current carrying filamentary conductor *AB* carrying current *I* along *Z* axis with its upper and lower ends subtending angles α_1 and α_2 respectively. 7