

**Digital Signal Processing**  
**(EC-308, Dec-2007)**

**Note:** Section A is compulsory. Attempt any four questions from Section-B and any two from Section-C.

**Section-A**

1. a) What are the constraints on the transfer function if it were to represent a casual LTI system?
- b) What is the relationship between the Z-transform and the discrete Fourier transform?
- c) In what respect does DFT differ from continuous Fourier transform?
- d) Explain the symmetry properties of DFTs which provide basis for fast algorithms.
- e) State the final value theorem of Z-transform.
- f) Mention two symmetry properties of FIR filters for obtaining linear phase.
- g) State the desirable characteristics of windows in the design of FIR digital filters.
- h) What is frequency warping in Bilinear transformation?
- i) What is the difference between Butterworth and chebyshev filters in terms of frequency response.
- j) Explain the concept of pipelining in DSP processor.

**Section-B**

2. What is the frequency response of a discrete LTI system? Derive the frequency response of a system whose impulse response is given by  
 $h(n) = a^n U(n-1)$  for  $|a| < 1$
3. Find the inverse of Z-transform of the function.  $X(z) = \frac{(z-4)}{(z-1)(z-3)^2}$  for  $|z| > 2$
4. draw a 8-point radix-2 FFT DIT flow graph and obtain DFT of the following sequence  $x(n) = (0, 1, -1, 0, 0, 2, -2, 0)$
5. Design flow pass FIR filter using Hamming window to meet the following specifications.  
 $H(\omega) = 1$  for  $0 \leq \omega \leq \pi/6$   
 $= 0$  for  $\pi/6 \leq \omega \leq \pi$   
Use a 10 tap filter and obtain the impulse response of the desired filter.
6. Which is more sensitive network to finite word length?  
(a) Direct form-II  
(b) Cascade form  
Justify your answer

**Section-C**

7. AN IIR low-pass filter is to be designed to meet the following specifications:  
(a) pass-band frequency: 0 to 1.2 k Hz  
(b) Stop band edge: 2 k Hz  
(c) pass-band attenuation  $\leq 0.5$  db  
(d) stop band attenuation  $\geq 15$  db  
Using butter worth approximation and bilinear transformation obtain the desired IIR digital filter.
8. A LTI system is described by  $y(n) = y(n-1) - 0.24 y(n-2) + x(n)$   
Find the response of this system for an input of  $x(n) = 10 \cos(0.05\pi n)$
9. With the help of a block diagram, explain the architecture of a TMS processor.